

Polar diagram X-Treme 25 vs. MaxFun 25

■ : Figures X-Treme 25
■ : Figures MaxFun 25

TWS	6 kts		8 kts		10 kts		12 kts		14 kts		16 kts		20 kts	
TWA	X-Treme 25	MaxFun 25	X-Treme 25	MaxFun 25	X-Treme 25	MaxFun 25	X-Treme 25	MaxFun 25	X-Treme 25	MaxFun 25	X-Treme 25	MaxFun 25	X-Treme 25	MaxFun 25
52	6.14	5.05	6.79	5.87	7.1	6.18	7.35	6.36	7.55	6.48	7.72	6.54	8	6.6
60	6.44	5.37	7.15	6.14	7.51	6.46	7.8	6.64	8.07	6.77	8.32	6.85	8.77	6.94
75	6.69	5.73	7.54	6.37	7.96	6.85	8.37	7.08	8.77	7.25	8.10	7.39	9.9	7.59
90	6.64	6.13	7.73	6.57	8.37	6.88	8.97	7.39	9.55	7.73	10.09	7.96	11.09	8.35
110	6.88	6.2	7.7	6.85	8.83	7.23	9.59	7.59	10.29	7.96	10.99	8.34	12.23	9.38
120	6.69	5.99	7.88	6.81	8.76	7.42	9.63	7.88	10.49	8.37	11.96	8.88	14.54	9.86
135	6.02	5.36	7.15	6.3	8.33	7.03	9.85	7.86	11.01	8.9	12.06	8.74	14.01	10.98
150	4.88	4.47	6.2	5.48	7.14	6.21	8.14	6.84	9.51	7.49	14.58	8.58	14.58	10.86
Up.Vs	5.51	4.56	6.02	5.23	6.17	5.49	6.29	5.63	6.41	5.71	6.52	5.76	6.73	5.81
Up.Bt	43.2	43.9	39	41.3	37.3	39.3	37.3	38.1	36.9	37.5	37.1	37.3	37.9	37.9
Dn.Vs	5.55	4.96	6.29	5.71	7.25	6.07	9.14	6.3	10.75	6.77	12.08	9.49	14.65	11.23
Dn.Bt	141.9	141	148.8	146	148.7	153	141.7	162	142.2	166	145.1	142	149.6	147